

Bosch AL1814CV, 2 607 225 727, PCB 1607502501-A, 02-2017

Resistors		
	Value	Case
R1	NTC 15D-7	ø7 mm
R2	680k, 1%	TH 1/4W
R3	510k, 1%	TH 1/4W
R4	510k, 1%	TH 1/4W
R5	22k, 1%	TH 1/4W
R6	3R6, 1%	TH 1/4W
R7	30R, 1%	TH 1/4W
R8	100R, 1%	TH 1/4W
R9	200k, 1%	TH 1/4W
R10	120R, 1%	TH 1/4W
R11	4R7, 1%	TH 1/4W
R12	10k, 1%	TH 1/4W
R13	1k, 1%	TH 1/4W
R14	4R7, 1%	TH 1/4W
R15	10R, 1%	TH 1/4W
R18	430R, 1%	TH 1/4W
R19	120R, 1%	TH 1/4W
R20	1k, 1%	TH 1/4W
R21	1k, 1%	TH 1/4W
R22	1k, 1%	TH 1/4W
R23	1k8, 1%	TH 1/4W
R24	0R22, 1%	TH 1/4W
R25	0R22, 1%	TH 1/4W
R26	1k, 1%	TH 1/4W
R27	620k, 1%	TH 1/4W
R28	20k, 0.5%	TH 1/4W
R29	10k, 1%	TH 1/4W
R30	10k, 1%	TH 1/4W
R31	10R, 1%	TH 1/4W
R32	430k, 1%	TH 1/4W
R33	6k04, 1%	TH 1/4W
R34	12k, 1%	TH 1/4W
R35	33k, 1%	TH 1/4W
R36	10k, 1%	TH 1/4W
R37	680R, 1%	TH 1/4W
R38	1k, 1%	TH 1/4W
R39	12k, 1%	TH 1/4W
R40	10k, 1%	TH 1/4W
R41	8k25, 0.5%	TH 1/4W
R42	10k, 1%	TH 1/4W
R43	10k, 1%	TH 1/4W
R44	20k, 0.5%	TH 1/4W


Capacitors		
	Value	Case
C1	0.47uF X2 MPX 275V	TH 18x17x7.5mm
C2	33uF, 400V, ELKO	TH 27x16mm
C3	1.5nF	TH 3.5x3mm
C4	3.3nF, 500V	TH ø8mm
C5	100nF	TH 3.5x3mm
C6	10nF	TH 3.5x3mm
C7	2,2nF X1 400VAC, Y1 250VAC	TH ø10 mm
C8	2,2nF X1 400VAC, Y1 250VAC	TH ø10 mm
C9	1nF	TH ø5 mm
C10	330uF, 35V, ELKO	20 x 10mm
C12	100uF, 35V, ELKO	TH 12 x 8mm
C13	1nF	TH ø5 mm
C14	10nF	TH 3.5x3mm
C15	10nF	TH 3.5x3mm
C16	1.5nF	TH 3.5x3mm

Diodes & Transistors		
	Value	Case
V1	1N4007	DO-41
V2	1N4007	DO-41
V3	1N4007	DO-41
V4	1N4007	DO-41
V5	2N3904	TO-92
V6	MMF80R900P, F3NK80Z	TO-220F, TO-220FP
V7	UF4007	DO-41
V8	1N4148	DO-35
V9	1N4007	DO-41
V10	ER502	DO-201AD
V12	1N5819	DO-41
V13	BC546	TO-92
V14	1N4148	DO-35
V15	1N4148	DO-35
V16	BZX15	DO-35
V17	BZX27	DO-35
V18	SB340	DO-201AD
V19	LED Green	5mm
V20	BC546	TO-92

Integrated Circuits		
	Value	Case
N1	LM324AN	DIL14
N2	TL1431	TO-92
D1	07502233	DIL16
U2	817A	DIP4
U3	817A	DIP4

Miscellaneous		
	Value	Case
F1	Fuse T 1.25A	8.5mmx8.5mm
L1	F-TC4701-0001	
TR1	F-TXFORMER---117	

Tr1, F-TXFORMER---117



\*TH Through Hole component